

## RT-B71/BC/INT



### INTERNAL BATTERY CHARGER +2 1.2AH WITH B70/2DC/BOX

Kit for emergency batteries charger for brushless digital controller B70/2DC/BOX 24Vdc with plug-in card, with 2 recovery batteries 12Vdc, 1.2 Ah. Box case included.

#### FEATURES

- Kit for emergency batteries charger for brushless digital controller B70/2DC/BOX 24V DC with plug-in card, with 2 recovery batteries 12V DC, 1.2 Ah.
- Box case included.

#### TECHNICAL INFORMATION

- Power line supply: 16vac ... 24vac
- Operating temperature: -20°C +55°C
- Maximum input power: 15W
- Lead-acid batteries: 2 x 12vdc 1200mAh, connected in series (external B71/B)
- Nominal charge voltage: 27.6Vdc
- Minimum self-protection voltage of battery: 19.5Vdc
- "br" open jumper charge current: 250 mA (for 1200mah batteries)
- "br" close jumper charge current: 400 mA (optional, for fast charge of 4500mAh batteries) - B71/BC/EXT
- Maximum dimension product in mm (L x W x H): 243 x 49 x 89
- Product weight packed (Kg): 1.5