

## RT-B71/BCHP/EXT



### RECOVERY BATTERY CHARGER +2 4.5AH WITH B70/2DCHP-B70/LDCHP

Kit for emergency batteries charger for brushless digital controller EDGE1/BOX - B70/1DCHP 36V DC with plug-in card, with 2 recovery batteries 12Vdc, 4.5 Ah. Box case included.

#### FEATURES

- Kit for emergency batteries charger for brushless digital controller EDGE1/BOX - B70/1DCHP 36V DC with plug-in card, with 2 recovery batteries 12V DC, 4.5 Ah.
- Box case included.

#### TECHNICAL INFORMATION

- Power line supply: 16vac ... 24vac
- Operating temperature: -20°C +55°C
- Maximum input power: 15W
- Lead-acid batteries: 2 x 12vdc 4500mAh, connected in series (external B71/B)
- Nominal charge voltage: 27.6 Vdc
- Minimum self-protection voltage of battery: 19.5Vdc
- Charge current: 400 mA
- Product weight packed (Kg): 5.2